



Nymi Connected Worker Platform Release Notes

CWP 1.2.0

2021-12-16 v2.0

Contents	2
Table 1: Revision History	3
Nymi Connected Worker Platform 1.2.0	4
Nymi Connected Worker Platform components	4
Nymi Documentation Package	4
NFC Reader Support	5
New In This Release	5
Health Attestation	5
Skin Temperature Alert	5
Contact Tracing Update	6
Increased Scalability	6
Backwards Compatibility	7
Table 2: Backwards Compatibility Table	7
Known Issues	8
Table 3: Known Issues in CWP 1.2.0	8
Table 4: Resolved Issues in CWP 1.2.0	9
Table 5: Known Issues in CWP 1.1.x	10
Table 6: Known Issues in NEE 3.3.0	14
Table 7: Known Issues for NEE 3.2.1	15
Appendix 1: Documentation Package for CWP 1.2.0	16
Core Documentation	16
Table 8: Core Product Documentation	17
Secondary Documentation	18
Appendix 2: NFC Readers Tested for CWP 1.1.0	19
Table 9: NFC Readers	19

Table 1: Revision History

Version	Date	Revision History
01	Dec 15, 2021	First release of document
02	Dec 16, 2021	Update the build version of CWP backend components



Nymi Connected Worker Platform 1.2.0

Nymi's Connected Worker Platform (CWP) connects people with technology through safe, simple, and secure solutions. The Connected Worker Platform supports numerous use cases and digital systems and combines point solutions into a single offering.

The goal of the Connected Worker Platform is to simplify the connection of workers to the digital space found in modern organizations. When the barriers to secure digital work are removed, workers can focus on what they do best.

CWP 1.2.0 is the second major update to Nymi's Connected Worker Platform. In this release, Nymi introduces two features to the safe office use cases to help employees' safe returning to the office. The health attestation feature ensures that employees who have high risk of carrying contagious diseases do not enter the office. The skin temperature alert feature notifies employees of their abnormal body temperature.

Nymi Connected Worker Platform components

CWP 1.2.0 includes the following component versions:

- Nymi Band™ 3.0
- Firmware version of Nymi Band 3.0– 4.2.7.10
- Nymi Band Application–4.1.0.6
- Nymi Lock Control–3.4.0.2
 - With Nymi SDK – 5.8.0.749
- Nymi Enterprise Server–4.1.0.5
- Nymi Enterprise Server Auto Deployment Scripts– 1.2.3
- Nymi SDK –5.9.0.4
- CWP backend components – 1.2.0.62
- Nymi Data Exchange Service Edge Agent -1.0.0.13

Nymi Documentation Package

For information on the documentation available for the CWP 1.2.0 release, see [Appendix 1](#).



NFC Reader Support

NFC reader support is not tested under the CWP 1.2.0 release. For NFC readers supported in the previous CWP releases see [Appendix 2](#).

New In This Release

Health Attestation

The Health Attestation use case reduces infection spread by encouraging employees to be aware of their health before they go to work. It features the Nymi Health Check web application that walks an employee through a health self-assessment questionnaire. The responses indicate if the employee should stay at home or proceed to the office. The employee confirms a positive (healthy) self-assessment on the Nymi Band which enables HID Seos.

Health Attestation ensures that the employees who are entering the office do not have any symptoms. Employees answer questions on the Nymi Health Application from a web browser. If the employee indicates that they do not have any symptoms, they will be allowed to enter the office. Otherwise, they will be instructed to contact the health and safety staff to undergo a secondary screening. The health and safety staff can use the Nymi Health Application to access employees' attestation history and record secondary screening results.

After completing the health attestation in the Health Check Application, the employees who are permitted to enter the office will then respond to a Health Check question on their Nymi Band. Their response will allow them to gain access to the office by tapping their Nymi Bands on SEOS enabled door readers. The employees must respond to the Health Check question every time they authenticate to the Nymi Band, to gain access to the office through a SEOS enabled door. The responses to the Health Check question are collected by the Nymi Data Exchange Service. The Health Check question can be enabled through the NES Administrator Console.

Skin Temperature Alert

The Temperature Alerting use case reduces infection spread by detecting elevation in skin temperature, which can be a symptom of infection. The Nymi Band uses its on-board temperature sensors with an



anomaly detection algorithm to generate an alert for the user in the event an elevated temperature is detected. The user is instructed to seek secondary screening. A health administrator records the secondary assessment in the Nymi Health Check web application.

The Nymi Band continuously monitors the users' wrist temperature. If the Nymi Band detects the users' wrist temperature exceed a normal range for an extended period of time, it delivers a high temperature alert and then prompts the user to contact health and safety staff. Temperature alerts are logged by the Nymi Data Exchange Service. No actual temperature data ever leaves the Nymi Band. The Nymi Band is not a medical device, and it does not report the skin temperature or fever. The Temperature Alert can be enabled through the NES Administrator Console.

The True Positive Rate (TPR) of the Skin Temperature Alerting feature could not be validated in time for this release. Therefore, this feature is marked as experimental until such validation can be completed in a suitable environment.

Contact Tracing Update

The Contact Tracing solution has been updated to stay current with the latest CDC contact tracing guideline. Close contact events are reported if two Nymi Bands are in proximity for a cumulative total of 15 minutes or more over a 24-hour period.

The contact tracing dashboard received updates to improve usability and to help the Health and Safety staff perform contact tracing more easily.

Increased Scalability

This release increases the capacity of the infrastructure to support 3,000 active employees.

For more information about these features, see the *Nymi Overview Guide*.

Backwards Compatibility

Table 2: Backwards Compatibility Table

			Nymi Infrastructure									
			NEE 2.3.1	NEE 2.4	NEE 2.5	NEE 2.6	NEE 3.0	NEE 3.1	NEE 3.2	NEE 3.3	CWP 1.1.x	CWP 1.2
Nymi Band Firmware	Nymi Band 2.0	NEE 2.3.1	•	•	•	•						
		NEE 2.4	•	•	•	•						
		NEE 2.5	•	•	•	•		•	•	•		
		NEE 2.6	•	•	•	•		•	•	•		
	Nymi Band 3.0	NEE 3.0					•					
		NEE 3.1	•	•	•	•		•				
		NEE 3.2	•	•	•	•			•	•		
		NEE 3.3	•	•	•	•			•	•		
		CWP 1.1.x									•	
		CWP 1.2										•

Legend:

• Compatible

☐ Not compatible (empty box)

Table 3: Known Issues in CWP 1.2.0

The following section lists known issues as of the CWP 1.2.0 release.

Issue Number	Description
CWP-1931	<p>Issue: When the user is signed into Health Check App across multiple device or in multiple browsers. Signing out in one session does not automatically sign out all the other sessions.</p> <p>Workaround: Ensure the user signs out across all devices or close all browsers.</p>
CWP-2018	<p>Issue: The contact tracing information for a Nymi Band cannot be displayed when the Nymi Band is deleted in NES</p> <p>Workaround: First look up the MAC address of the deleted Nymi Band from the NES database, Nymi Band audit record. Then in the CT database, look up the contact events registered to that MAC address.</p>
DCS-253	<p>Issue: When viewed on certain browsers, the Contact Tracing Dashboard's Most Contact Employees graph does not zoom properly.</p> <p>Workaround: Return the browser to 100% zoom.</p>
LC-797	<p>Issue: Unlocking the PC by NFC tap fails if the network connection to NES is unavailable.</p> <p>Workaround: Unlocking the PC by typing in username then hit enter key or by tapping the Nymi Band on the Bluetooth adapter (if BLE tap is enabled).</p>
LC-827	<p>Issue: The Lock Control does not contain the same SDK as the SDK released in CWP 1.2.0. The functionality of the Lock Control is not impacted. When updating from an earlier version, the SDK might not be automatically updated.</p> <p>Workaround: For new install or update, first install the Nymi SDK, then run the Lock Control installer.</p>
NEM-2738	<p>Issue: When updating the NES, at the Review Settings tab the installer may give a database login error.</p> <p>Workaround: Navigate to the Database tab and click the Test button. Then go back to Review Settings tab and click Test.</p>

NEM-2744	<p>Issue: The NES command prompt install tool fails when encryption is set to "None".</p> <p>Workaround: Deploy or update NES either use NES installer executable or the NES auto deploy script.</p>
NEM-2546	<p>Issue: When the user selects the Contact Support option from the Lock Control tray icon, a zip file of logs is generated but the location of the zip is not provided.</p> <p>Workaround: See the documentation for the location of the zip file.</p>
NEM-2747	<p>Issue: When updating the NBA to CWP 1.2.0, the installer does not automatically update the SDK to the latest version. Without updating the SDK, user might encounter errors during enrollment.</p> <p>Workaround: Before upgrading the NBA, uninstall SDK that exists on the terminal.</p>
SKD5-1803	<p>Issue: Nymi runtime fails to install when installing to a non-default location.</p> <p>Workaround: Install the Nymi runtime at its default location: "C:\Program Files\Nymi"</p>
SDK5-1839	<p>Issue: Occasionally, CWP data is not retrieved by the edge agent while the Nymi Band is on charger.</p> <p>Workaround: The data will be retrieved when the Nymi Band is authenticated.</p>
SDK5-1854 SDK5-1855	<p>Issue: nbed cannot be upgraded or uninstalled from some models of thin clients.</p> <p>Workaround: Uninstall the nbed by reset the thin client. To upgrade the nbed, reset the thin client to a standard image and then install the newer version of nbed.</p>

Table 4: Resolved Issues in CWP 1.2.0

The following known issues were resolved in the CWP 1.2.0 releases.

Issue Number	Description
DCS-260	<p>Issue: log4j CVE-2021-44228 vulnerability</p>
CWP-1081	<p>Issue: If a user re-enrolls to a different Nymi Band, then any new contact data they collect will not show up for 24 hours in the dashboard.</p> <p>Workaround: Wait 24 hours for the data to update or restart the CTCA.</p>

CWP-1059	<p>Issue: On the Contact Tracing dashboard, when searching for contact events by contact date, not all events may be returned for a specified day.</p> <p>Workaround: Add one day to the end of the date range specified in order to ensure that all data is returned.</p>
CWP-1014	<p>Issue: The Contact Tracing dashboard label for Contact Time, erroneously indicates that time is shown in UTC time zone.</p> <p>The time is shown is the local time of the web browser. This is a cosmetic issue that does not affect data.</p>
NEM-2270, NEM02280, NEM-2296	<p>Issue: In some cases, after logging in to the NES Admin Console, the console page does not show that login succeeded.</p> <p>Workaround: Navigate to another page to confirm that login was successful.</p>
NF-3739	<p>Issue: In some cases, the firmware updater program may not make use of all available BLE adapters.</p> <p>Workaround: If this issue occurs, stop and restart the updater.</p>

Table 5: Known Issues in CWP 1.1.x

The following known issues were reported in the CWP 1.1.x releases.

Issue Number	Description
DCS-260	<p>Issue: log4j CVE-2021-44228 vulnerability</p>
CWP-1157	<p>Issue: If multiple Nymi Bands are placed on the charger simultaneously, the Contact Tracing Collection Agent (CTCA) may not retrieve the contract events from all the Nymi Bands.</p> <p>Workaround: Take the Nymi band off the charger and the contact events will be retrieved by CTCA.</p>
CWP-1081	<p>Issue: If a user re-enrolls to a different Nymi Band, then any new contact data they collect will not show up for 24 hours in the dashboard.</p> <p>Workaround: Wait 24 hours for the data to update, or restart the CTCA.</p>
CWP-1059	<p>Issue: On the Contact Tracing dashboard, when searching for contact events by contact date, not all events may be returned for a specified day.</p>

Issue Number	Description
	<p>Workaround: Add one day to the end of the date range specified in order to ensure that all data is returned.</p>
CWP-1024, CWP-1012	<p>Issue: In a multi-domain environment, the Contact Tracing dashboard only shows data from users in one domain.</p> <p>Workaround: Ensure that all users of the Contact Tracing feature are in the same domain.</p>
CWP-1017	<p>Issue: The Contact Tracing Collection Agent (CTCA) may take a long time to initialize the API.</p> <p>This is a benign issue as no data is lost.</p>
CWP-1015	<p>Issue: Multi-instance functionality for CTCA is not currently supported. If multiple instances of the CTCA are started, errors will occur and only one of the instances will function correctly.</p>
CWP-1014	<p>Issue: The Contact Tracing dashboard label for Contact Time, erroneously indicates that time is shown in UTC time zone.</p> <p>The time is shown is the local time of the web browser. This is a cosmetic issue that does not affect data.</p>
CWP-1008	<p>Issue: The format of the login name for the Contact Tracing dashboard is different from the format required by other Nymi product logins.</p> <p>Workaround: Ensure the login name is entered in the appropriate format: <username>@example.domain.name</p>
CWP-1004	<p>Issue: There is no input validation on user-specified queries for the Employee Timeline graph on the Contact Tracing dashboard. If an invalid query is entered, a blank graph is returned.</p>
CWP-1000	<p>Issue: On the Contact Tracing dashboard, the Update button for the Most Contacted Employee Details does not update the view.</p> <p>Workaround: Refresh the page to update the view.</p>
CWP-926	<p>Issue: The contact tracing dashboard does not indicate when the display is blank because there is no data in the database. This is a cosmetic issue and does not affect functionality.</p>

Issue Number	Description
CWP-691	<p>Issue: Spurious warning messages about <i>ctca.properties</i> appear in the log when the configuration is correct. These warnings can be safely ignored. (This issue is only applicable for CWP 1.1.x)</p>
CWP-570	<p>Issue: On the Contact Tracing dashboard, the list of user contact events in the User Timeline is not paginated.</p> <p>Workaround: If too many results are returned, filter the search query to narrow the results.</p>
CWP-569	<p>Issue: On the Contact Tracing dashboard, the axis labels for Unique Contact Count stack on top of each other, making the text illegible. This is a cosmetic issue that does not affect the data.</p>
NEM-2660	<p>Issue: On Windows Server 2019, the SQL Express 2012 installer included in the NES installer may fail.</p> <p>Workaround: Install SQL Express 2017 in Basic mode before running the NES installer on Windows Server 2019.</p>
NEM-2651	<p>Issue: The <i>NesSupportTool.exe</i> is not able to extract and create a log zip file on Windows Server 2019.</p>
NEM-2632	<p>Issue: The <i>.ninst</i> file generated by NES is not self-documented. Contact Nymi Support for any <i>.ninst</i> file related questions.</p>
NEM-2553	<p>Issue: Running the NES install.exe program for a second time causes a disabled NES Installer Maintenance dialog to appear.</p> <p>Workaround: None. This dialog does not require user intervention.</p>
NEM-2270, NEM02280, NEM-2296	<p>Issue: In some cases, after logging in to the NES Admin Console, the console page does not show that login succeeded.</p> <p>Workaround: Navigate to another page to confirm that login was successful.</p>
NEM-1750	<p>Issue: Any interruption in network connectivity during enrollment causes the system to become out of synch.</p> <p>Workaround: If network connectivity is lost during enrollment, perform a Delete User Data operation on the Nymi Band, disconnect the device from the user in the NES Admin Console, and restart enrollment.</p>

Issue Number	Description
NPM-363	<p>Issue: By design, the Nymi Band firmware will not record a Proximity Event during the time that the Collection Agent is connected to download Proximity Events. In some rare cases, this can lead to a missed Contact Event.</p>
SDK5-1729	<p>Issue: While using Lock Control, if a user moves their Nymi Band within 10cm of the BLE adapter, a login or unlock will occur even if that was not the user's intent. For example, this may occur if a user is reaching past the adapter to plug in a charger or access a USB hub.</p> <p>This is a benign issue and does not affect the behaviour of the system.</p>
LC-785	<p>Issue: When a user without an active Nymi Band registered in NES attempts an NFC tap to unlock or login, no error message is shown.</p> <p>This is a benign issue as the NFC tap is expected to fail when the Nymi Band is deactivated in NES.</p>
NF-3748	<p>Issue: In some rare instances, users may experience consecutive authentication failures due to the ECG measurement during Liveness Detection.</p> <p>Workaround: If required, Liveness Detection can be disabled. See NF-3733 for important considerations before using this workaround.</p>
NF-3745	<p>Issue: The fingerprint sensor does not respond to the user placing their finger on the sensor. Authentication times out.</p> <p>Workaround: In this scenario, authentication failure now occurs quickly, and the user can retry authentication with a high chance of success.</p>
NF-3741	<p>Issue: In some cases, the firmware update may take longer than 300 seconds.</p>
NF-3739	<p>Issue: In some cases, the firmware updater program may not make use of all available BLE adapters.</p> <p>Workaround: If this issue occurs, stop and restart the updater.</p>
NF-3738	<p>Issue: In some rare instances, the fingerprint sensor may not respond while a user is attempting to register their fingerprint template.</p> <p>Workaround: Remove the Nymi Band from the wrist. Put the Nymi Band back on and restart the enrollment process.</p>
NF-3733	<p>Issue: When Liveness Detection is disabled in the NES Policy, it is possible for users to authenticate the Nymi Band on objects other than a human body if the</p>

Issue Number	Description
	<p>correct fingerprint is provided. This is a known and expected side effect of disabling Liveness Detection.</p> <p>Workaround: Liveness Detection should be disabled only in environments where users are having difficulty authenticating due to liveness and no other remedy has resolved their issue.</p>
NF-3724	<p>Issue: In some rare cases, when using the firmware updater to update the firmware on a Nymi Band that is in Recovery mode, the update may fail on the first attempt.</p> <p>Workaround: No user intervention is required. The updater continues to retry the update until it is successful.</p>
NF-3694, NF-3693, NF-3687	<p>Issue: In some cases, when using the Nymi Band as a FIDO2 security key to sign into a Windows PC, the user may have to hold their Nymi Band over the NFC reader for up to 400ms.</p> <p>If this issue occurs, a full authentication may take up to 2000ms.</p>

Table 6: Known Issues in NEE 3.3.0

The following known issues were reported in the NEE 3.3.0 release.

Issue Number	Description
NEM-2643	<p>Issue: If the Nymi Band Application loses the network connection or if the app is closed during the fingerprint enrollment process, the Nymi Band and the application will become desynchronized, and enrollment is interrupted.</p> <p>Workaround: If this issue is encountered, the user must Delete User Data and start the enrollment process again.</p>
NEM-2453	<p>Issue: When upgrading NES from NEE 2.6.X to NEE 3.3.0, if the NES Admin Console is left open in a browser page, there can be deprecation in functionality. The logout button will not work.</p> <p>Workaround: Before performing an upgrade of NES, close all browsers with the NES Admin Console open.</p>

Table 7: Known Issues for NEE 3.2.1

The following known issues were reported in the NEE 3.2.1 release.

Issue Number	Description
SOL-365	<p>Issue: During the import of the <i>fullchain.p12</i> file, no keys are found for the certificate during the NES installation. While <i>certlm.msc</i> displays a private key icon next to the NES L2 certificate, Windows is not able to access the private key. This results in a failure on the NES diagnostics page indicating that there was an error generating test certificates.</p> <p>Workaround: Delete the entire certificate chain and then re-import the fullchain.p12 (right click - import PFX) resulting in the cert chain AND key being successfully imported. If the IIS application pool identity used by NES is not "LOCAL SYSTEM", then move the NES L2 certificate to the Intermediate CA certificate store, and run "iisreset".</p>
NEM-2302	<p>Issue: Previously configured database logins are not saved in the generated .ninst file when loaded from a previous installation.</p> <p>Workaround: To generate a complete .ninst file, Export Settings immediately after completing a fresh installation of NES.</p>
NEM-2295	<p>Issue: NES does not have sufficient Application Pool identity permissions to support the infrastructure (NEA certificate generation, look-ups, etc.).</p> <p>Workaround: Change the Application Pool identity setting to LocalSystem.</p>
NEM-2249	<p>Issue: In the NES GUI installer, the user is unable to edit Database login details after initial entry of details.</p> <p>Workaround: Use the original database user details entered for the new user/auditor, or close and restart the NES installer.</p>
NEM-2439	<p>Issue: Completing a NES installation with a specific user account specified for the Application Pool identity, where the user account which does not have Database</p>

Issue Number	Description
	<p>privileges, results in database errors when running tests on the database page in the NES installer.</p> <p>Workaround: If a NES installation is completed by a user who does not have Database permissions, complete the installation without running tests on the Database page of the installer.</p>
SDK5-1618	<p>Issue: When upgrading the Nymi runtime from NEE 2.6 to NEE 3.2, the Nymi Websocket API stops working.</p> <p>Resolution: Replace the original nymi_agent.toml file with the nymi_agent.toml file from the NEE 3.2.1 package.</p>
NEM-1954	<p>Issue: To configure hardening on NES, configure the NES to use LocalSystem identity from the Application Pool Identity list. This can be changed on the IIS page in the NES installer.</p>

Appendix 1: Documentation Package for CWP 1.2.0

Documentation for the Nymi Connected Worker Platform can be found in the release package delivered for CWP 1.2.0.

Core Documentation

The following documentation is provided with the standard CWP 1.2.0 package. This table identifies revisions to documentation since the last release package.

Table 8: Core Product Documentation

Document Title	Version	Reference	Modifications
Nymi Connected Worker Platform Release Notes 1.2.0	1.0	Nymi_Connected_Worker_Platform_Release_Notes_1.2.0.pdf	Release notes for CWP 1.2.0
Nymi Overview Guide	5.0	NymiOverviewGuide_V5.pdf	Update for the Connected Worker Platform 1.2.0 release.
Nymi Deployment Guide	6.0	NymiDeploymentGuide_V6.pdf	Update for the Connected Worker Platform 1.2.0 release.
Nymi Administration Guide	6.0	NymiAdministrationGuide_V6.pdf	This update includes information to support Health Attestation, Temperature Alert, and Data Exchange Service.
Nymi SDCT Install and Config Guide	3.0	NymiSDCTInstallandConfigGuide_V3.pdf	Update for the CWP 1.2.0 release.
Nymi Troubleshooting Guide	6.0	NymiTroubleshootingGuide_V6.pdf	Update for the CWP 1.2.0 release.
Nymi Band Regulatory Guide	2.1	NymiBandRegulatoryInformationGuide_V2_1.pdf	No modifications.
Nymi Third Party Licenses	5.0	NymiThirdPartyLicenses_V5.pdf	Updated with new licenses.
Nymi API WebSocket Interface Guide	3.0	NymiAPIWebSocketInterfaceGuide_V3.pdf	No modifications.
Nymi API C Interface Guide	3.0	NymiAPICInterfaceGuide_V3.pdf	No modifications.

Document Title	Version	Reference	Modifications
Nymi API for Linux Guide	3.0	NymiAPILinuxGuide_V3.pdf	No modifications.

Secondary Documentation

The secondary documents offer additional support for the CWP 1.2.0 solution. These documents are not included in the CWP 1.2.0 package.

To access all the secondary documents, visit:

<https://support.nymi.com/hc/en-us/sections/360012100892-Supplementary-Product-Documentation>

Appendix 2: NFC Readers Tested for CWP 1.1.0

Nymi includes dedicated NFC reader compatibility testing as part of its release testing. The following table covers the specific NFC reader models tested for compatibility with CWP 1.1.0. Note that the level of ongoing testing is indicated as follows:

1. Recommended Readers - best performance; testing planned with every CWP release going forward from CWP 1.1.0.
2. Supported Readers - meet specific use cases but may not perform as well as a recommended reader; testing planned with every CWP release going forward from CWP 1.1.0.
3. Verified Readers - tested against a minimum of one NEE or CWP release; additional testing may be required to support additional releases; will be tested as part of the customer upgrade process.

Table 9: NFC Readers

NFC Reader Model	Status
HID Omnikey 5022	Recommended
ACS ACR122U	Verified with NEE 3.3.0
Systec CONNECT BOX	Verified with NEE 3.3.0
Elatec TWN4 LEGIC NFC USB	Verified with NEE 3.3.0
HID Omnikey 5127CK Mini	Verified with NEE 3.2.0
ACS ACR1252U	Verified with NEE 3.2.0
Identiv CLOUD/uTrust 3700 F	Verified with NEE 3.2.0



Copyright © 2021

Nymi Inc. All rights reserved.

Published in December 2021

Nymi Inc. (Nymi) believes the information in this document is accurate as of its publication date. The information is subject to change without notice.

The information in this document is provided as-is and Nymi makes no representations or warranties of any kind. This document does not provide you with any legal rights to any intellectual property in any Nymi product. You may copy and use this document for your referential purposes.

This software or hardware is developed for general use in a variety of industries and Nymi assumes no liability as a result of their use or application. Nymi, Nymi Band, and other trademarks are the property of Nymi Inc. Other trademarks may be the property of their respective owners.

Published in Canada.

Nymi Inc.

Toronto, Ontario

www.nymi.com