



NFC Reader Recommendations

Connected Worker Platform

V2.1

2024-03-20



Table of Contents

Revision History.....2

NFC Reader Recommendations.....3

 General Reader Requirements.....3

 Recommended NFC Readers3

 Verified NFC Readers.....3

 Unsupported NFC Readers5

Revision History

Date	Version	Revision History
April 04, 2023	1.0	Initial version.
April 11, 2023	1.1	Small fixes
October 19, 2023	2.0	Adding NFC reader and tablets to supported list
March 20, 2024		Adding the HID Omikey-5022 IP-67 IP-67 level rated variant to the recommend list



NFC Reader Recommendations

This document provides the supported technical specifications along with the NFC Readers that have been tested with the Nymi Band.

NOTE: If you want to use an NFC reader that is not listed in this article and supports the general reader requirements that are listed below, contact Nymi for more information regarding the NFC reader qualification process.

General Reader Requirements

In general, the minimum requirements of a Nymi Band-compatible NFC reader are:

- ISO14443A compatibility
- Operation frequency of 13.56MHz
- PC/SC compatibility

Recommended NFC Readers

Nymi recommends that customers use this reader in the Nymi Solution, based on its superior read range performance. This reader is tested with every release.

Use Case	NFC Reader Model
General Use	HID Omnikey 5022
Cleanroom	HID Omnikey 5022 IP-67 level rated variant

Verified NFC Readers

Nymi has tested and supports the NFC readers in supported releases, but the following NFC readers are not tested in every release.

Use Case	NFC Reader Model
General Use	ACS ACR122U
General Use	Elatec TWN4 MULTITECH 2 ¹ (Part Number:T4BT-FB2WEL7-M) Not FIDO 2 Compatible Elatec TWN4 MULTITECH 3 ¹ Elatec TWN4 LEGIC NFC USB (Part Number: T4DT-BB2BEL-NL)
Cleanroom	Elatec TWN4 MULTITECH 3 ¹ with the DS-TWN4-Silicone-Housing Elatec TWN4 LEGIC NFC USB (Part Number: T4DT-BB2BEL-NL) with the DS-TWN4-Silicone-Housing
Cleanroom / IPxx Rated / Single port BLE + NFC	Systec CONNECT BOX ²
General Use	HID Omnikey 5127CK Mini
General Use	Identiv CLOUD/uTrust 3700 F
General Use	ACS ACR1252U
General Use	RFIdeas WAVE ID Nano Vertical 13.56 MHz CCID USB Reader (SKU: RDR-7516AKU [USB-A], RDR-75U6AKU [USB-C])
General Use	RFIdeas WAVE ID Nano SDK 13.56 MHz CSN Black Vertical USB Reader (SKU: RDR-7512AKU [USB-A], RDR-75U2AKU [USB-C]) Not FIDO 2 Compatible
General Use	iDTRONIC NEO 2 HF NFC Desktop Reader (Part Number: R-DT-NEO2-HF)

1. At the time of placing your order, request firmware version WN4_xJx402_Y1SC160_Multi_CCID_1Slot_NYMI.bix
2. At the time of placing your order, request firmware version WN4_NJx402_Y1SC160_Nano_CCID_1Slot_NYMI_WIP0001.bix

Nymi has tested and supported the built-in NFC reader in these tablets.



Use Case	Model
General Use	Zebra ET80 tablet
General Use	Getac F110 (G6) tablet

Unsupported NFC Readers

The following readers are either incompatible with Nymi or have been discontinued.

Model	Status
HID Omnikey 5021	Discontinued
HID Omnikey 5025	Incompatible (operates at 125 kHz)